

DOE/NASA/20320-57  
NASA TM-83581

NASA-TM-83581

19840009411

# **A Mathematical Model for the Doubly-Fed Wound Rotor Generator**

## **Part II**

Frank J. Brady  
National Aeronautics and Space Administration  
Lewis Research Center

**LIBRARY COPY**

MAR 13 1984

LANGLEY RESEARCH CENTER  
LIBRARY, NASA  
HAMPTON, VIRGINIA

Work performed for  
**U.S. DEPARTMENT OF ENERGY**  
**Conservation and Renewable Energy**  
**Wind Energy Technology Division**

Prepared for  
Summer Meeting of the Power Engineering Society  
sponsored by the Institute of Electrical and Electronics Engineers  
Seattle, Washington, July 15-20, 1984

## DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Printed in the United States of America

Available from

National Technical Information Service  
U.S. Department of Commerce  
5285 Port Royal Road  
Springfield, VA 22161

NTIS price codes<sup>1</sup>

Printed copy: A02  
Microfiche copy: A01

<sup>1</sup>Codes are used for pricing all publications. The code is determined by the number of pages in the publication. Information pertaining to the pricing codes can be found in the current issues of the following publications, which are generally available in most libraries: *Energy Research Abstracts (ERA)*; *Government Reports Announcements and Index (GRA and I)*; *Scientific and Technical Abstract Reports (STAR)*; and publication, NTIS-PR-360 available from NTIS at the above address.

DISPLAY 49/2/1

84N17479\*# ISSUE 3 PAGE 1149 CATEGORY 33 RPT#: NASA-TM-83581

DOE/NASA/20320-57-PT-2 E-1972-PT-2 NAS 1.15:83581 CNT#:

DE-A101-76ET-20320 84/00/00 3 PAGES UNCLASSIFIED DOCUMENT

UTTL: A mathematical model for the doubly-fed wound rotor generator, part 2

AUTH: A/BRADY, F. J.

CORP: National Aeronautics and Space Administration, Lewis Research Center,  
Cleveland, Ohio. AVAIL. NTIS SAP: HC A02/MF A01

Proposed for presentation at the Summer Meeting of the Power Eng. Soc.,  
Seattle, 15-20 Jul. 1984; sponsored by IEEE

MAVS: /\*ELECTRIC GENERATORS/\*ROTORS/\*STATORS/\*WINDING

MINs: / ELECTRIC CURRENT/ ELECTRIC POTENTIAL/ MATHEMATICAL MODELS/ QUADRATURES

ABA: S.L.

ABS: A mathematical analysis of a doubly-fed wound rotor generator is  
presented. The constraints of constant stator voltage and frequency to the  
circuit equations were applied and expressions for the currents and  
voltages in the machine obtained. The derived variables are redefined as  
direct and quadrature components. In addition, the apparent (complex)  
power for both the rotor and the stator are derived in terms of these  
redefined components.

ENTER:



# **A Mathematical Model for the Doubly-Fed Wound Rotor Generator**

## **Part II**

Frank J. Brady  
National Aeronautics and Space Administration  
Lewis Research Center  
Cleveland, Ohio 44135

Work performed for  
U.S. DEPARTMENT OF ENERGY  
Conservation and Renewable Energy  
Wind Energy Technology Division  
Washington, D.C. 20545  
Under Interagency Agreement DE-AI01-76ET20320

Prepared for  
Summer Meeting of the Power Engineering Society  
sponsored by the Institute of Electrical and Electronics Engineers  
Seattle, Washington, July 15-20, 1984

*N84-17479#*



# A MATHEMATICAL MODEL FOR THE DOUBLY-FED WOUND ROTOR GENERATOR - PART II

Frank J. Brady

National Aeronautics and Space Administration  
Lewis Research Center  
Cleveland, Ohio 44135

**Abstract** - This paper is a mathematical analysis of a doubly-fed wound rotor generator. It is a continuation of a previous paper, which applied the constraints of constant stator voltage and frequency to the circuit equations and obtained expressions for the currents and voltages in the machine. In this paper the previously derived variables are redefined as direct and quadrature components. In addition, the apparent (complex) power for both the rotor and the stator are derived in terms of these redefined components.

## INTRODUCTION

In the previous paper [1], the doubly-fed wound rotor generator was analyzed. The machine included a three-phase winding on both the rotor and the stator. The general circuit equations were reduced to two simplified equations, one for the rotor voltage, another for the stator voltage.

Applying the constraints of constant stator voltage and frequency to these two circuit equations, it was possible to obtain the necessary rotor excitation. The current and voltage expressions, which resulted, were used to derive expressions for rotor and stator real powers; and also, to show the relationships between shaft, rotor, and stator powers. Those results will be used in this paper. However, the variables are redefined into direct and quadrature components. The expressions for apparent power on both the rotor and the stator are derived using these redefined components.

## SYMBOLS

$a$	ratio of stator number of turns to rotor number of turns
$e_R, e_S$	induced voltage, rotor, and stator, respectively
$e_{SD}, e_{SQ}$	induced stator voltage, direct, and quadrature components, respectively
$i_R, i_S$	instantaneous rotor and stator current, respectively
$i_{RO}$	rotor current required to generate open-circuit stator voltage
$i_{Re}$	rotor current required to compensate for stator impedance drop
$i_{RD}, i_{RQ}$	rotor current, direct and quadrature components, respectively

$K$	coupling coefficient
$L_R, L_S$	self inductance, rotor, and stator, respectively
$n_R, n_S$	number of turns, rotor, and stator, respectively
$R_R, R_S$	resistance of winding, rotor, and stator, respectively
$S$	slip
$t$	time
$V_R, V_S$	terminal voltage, rotor, and stator, respectively
$V_{RO}, V_{Re}$	rotor voltage required to establish $i_{RO}$ and $i_{Re}$ , respectively
$\bar{x}$	the bar above a variable indicates it is a phasor
$\theta_R, \theta_S, \theta_L$	phase angle shift, rotor, stator, and load, respectively
$\omega, \omega_S$	angular frequency, mechanical and synchronous electrical, respectively

## PREVIOUSLY DERIVED VARIABLES

Before proceeding with any new derivations, some of the results of the previous paper [1] will be restated. To make the development of the model easier to follow, some terms will be made more compact.

From the previous paper, the voltage and current at the stator terminals is,

$$\bar{v}_S = V_S e^{j(\omega_S t - \theta_R + \pi/2)} \quad (1-1)$$

and

$$\bar{i}_S = -I_S e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \quad (1-2)$$

The induced stator voltage was given as,

$$\frac{3}{2} a K L_R \frac{d}{dt} \left[ e^{j(\omega t/2)} \bar{i}_R \right] \quad (1-3)$$

This variable was not derived explicitly. But if the expression for  $\bar{i}_R$  is substituted into (1-3), the induced stator voltage becomes,

$$\bar{e}_S = V_S e^{j(\omega_S t - \theta_R + \pi/2)} + |Z_S| I_S e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \quad (1-4)$$

It should be noted that the derivative of the product in (1-3) produces the sum of two terms. The induced stator voltage is, more precisely,

$$\bar{e}_S = (1 - S)\bar{e}_S + S\bar{e}_S \quad (1-5)$$

Later in this paper, when the active and reactive powers are derived, this separation of terms will have more meaning.

The rotor variables that were previously derived are as follows:

Rotor current,

$$\begin{aligned} \bar{I}_R &= \bar{I}_{R0} + \bar{I}_{Re} \\ &= \frac{2}{3} \frac{1}{aKX_R} \left[ V_S e^{j(S\omega_S t - \theta_R)} + |Z_S| I_S e^{j(S\omega_S t + \theta_S - \theta_R - \theta_L)} \right] \end{aligned} \quad (1-6)$$

Rotor voltage,

$$\begin{aligned} \bar{V}_R &= \bar{V}_{R0} + \bar{V}_{Re} \\ &= \frac{2}{3} \frac{1}{aKX_R} |Z_R| \left[ V_S e^{j(S\omega_S t)} + |Z_S| I_S e^{j(S\omega_S t + \theta_S - \theta_L)} \right] \\ &\quad + \frac{3}{2} \frac{K}{a} S X_S I_S e^{j(S\omega_S t - \theta_R - \theta_L)} \end{aligned} \quad (1-7)$$

The voltage induced on the rotor is given by,

$$\frac{3}{2} \frac{K}{a} L_S \frac{d}{dt} \left[ e^{-j(\rho\omega t/2)} \bar{I}_S \right] \quad (1-8)$$

If the expression for  $\bar{I}_S$  is substituted into (1-8), the result is the induced rotor voltage,  $\bar{e}_R$ .

$$\bar{e}_R = \frac{3}{2} \frac{K}{a} S X_S I_S e^{j(S\omega_S t - \theta_R - \theta_L)} \quad (1-9)$$

In order to make the expressions for  $\bar{V}_R$  and  $\bar{I}_R$  more compact, the following definitions will be made:

$$I_{R0} = \frac{2}{3} \frac{1}{aKX_R} V_S \quad (1-10)$$

$$I_{Re} = \frac{2}{3} \frac{1}{aKX_R} |Z_S| I_S \quad (1-11)$$

$$E_R = \frac{3}{2} \frac{K}{a} S X_S I_S \quad (1-12)$$

When these definitions are substituted into equations (1-6) and (1-7), the results are,

$$\bar{I}_R = I_{R0} e^{j(S\omega_S t - \theta_R)} + I_{Re} e^{j(S\omega_S t + \theta_S - \theta_R - \theta_L)} \quad (1-13)$$

$$\begin{aligned} \bar{V}_R &= |Z_R| \left[ I_{R0} e^{j(S\omega_S t)} + I_{Re} e^{j(S\omega_S t + \theta_S - \theta_L)} \right] \\ &\quad + E_R e^{j(S\omega_S t - \theta_R - \theta_L)} \end{aligned} \quad (1-14)$$

#### ROTOR PHASOR DIAGRAM

Equations (1-13) and (1-14) describe the voltage and current as seen at the rotor terminals of the machine. Since these expressions are in phasor form, a phasor diagram can be constructed from them directly. This diagram is a visual aid to what happens on the rotor as slip and stator current varies. It will also be used to explain the basis for the direct and quadrature currents that will be derived later.

The phasor diagram (Fig. 1) shows the relative phase angles between the rotor variables. The reference phasor is  $\bar{V}_{R0}$ , since it was assumed to have zero phase angle. In order to draw the other variables, three assumptions must be made. First, the value of  $|Z_R|$  is arbitrary, but the relationship  $V_{R0} = |Z_R| I_{R0}$  must be maintained. Second, by manipulation of equations (1-10) and (1-11) it can be shown that the relationship  $I_{Re} = (|Z_S|/|Z_L|) I_{R0}$  must hold. Finally, the variable,  $E_R$  can be scaled using equation (1-12), and assuming that  $X_S \cong |Z_S|$ .




Figure 1. - Rotor phasor diagram. (Shown for positive slip.)

#### DIRECT AND QUADRATURE ROTOR CURRENTS

The induced stator voltage consists of two components, one that is in phase with the stator current, another leading the current by 90°. This can be shown by modifying equation (1-4). In order to make a comparison between voltage and current, the voltage must be placed in the same reference frame as the current. This is done by factoring equation (1-4) into the following form,

$$\bar{e}_S = \left[ V_S e^{j\theta_L} + |Z_S| I_S e^{j\theta_S} \right] e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \quad (2-1)$$



Comparing this equation to (1-2), it can be seen that both phasors  $\bar{e}_S$  and  $\bar{I}_S$  have the same rotational reference; namely,

$$e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)}$$

The terms within the brackets of equation (2-1) are the phasor components within the reference frame.

As they are written, the two components in equation (2.1) are not orthogonal. They can be made so by using the identity,

$$e^{j\theta} = \cos \theta + (\sin \theta)e^{j(\pi/2)} \quad (2-2)$$

and combining like components.

Equation (2-1) becomes

$$\begin{aligned} \bar{e}_S = & \left[ (V_S \cos \theta_L + R_S I_S) + (V_S \sin \theta_L + X_S I_S)e^{j(\pi/2)} \right] \\ & \times e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \end{aligned} \quad (2-3)$$

The first component is in phase with the stator current. It will be called the direct component, that is,

$$\begin{aligned} \bar{e}_{SD} = & (V_S \cos \theta_L + R_S I_S)e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \\ = & E_{SD}e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \end{aligned} \quad (2-4)$$

The second component leads the current by 90°. It will be called the quadrature component, that is,

$$\begin{aligned} \bar{e}_{SQ} = & (V_S \sin \theta_L + X_S I_S)e^{j(\pi/2)}e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \\ = & E_{SQ}e^{j(\omega_S t - \theta_R - \theta_L + \pi)} \end{aligned} \quad (2-5)$$

The components  $\bar{e}_{SD}$  and  $\bar{e}_{SQ}$  will be shown to have a relationship to the rotor current.

The expression for rotor current, equation (1-6) can be rewritten in the following form

$$\bar{I}_R = \frac{2}{3} \frac{1}{aKX_R} \left[ V_S e^{j\theta_L} + |Z_S| I_S e^{j\theta_S} \right] e^{j(\omega_S t - \theta_R - \theta_L)} \quad (2-6)$$

Using equality (2-2),  $\bar{I}_R$  can be separated into orthogonal components.

$$\begin{aligned} \bar{I}_R = & \frac{2}{3} \frac{1}{aKX_R} \left[ (V_S \cos \theta_L + |Z_S| I_S \cos \theta_S) \right. \\ & \left. + (V_S \sin \theta_L + |Z_S| I_S \sin \theta_S)e^{j(\pi/2)} \right] e^{j(\omega_S t - \theta_R - \theta_L)} \end{aligned} \quad (2-7)$$

If the appropriate substitutions are made, using equations (1-10) and (1-11), the rotor current becomes,

$$\begin{aligned} \bar{I}_R = & \left[ (I_{RD} \cos \theta_L + I_{Re} \cos \theta_S) \right. \\ & \left. + (I_{RD} \sin \theta_L + I_{Re} \sin \theta_S)e^{j(\pi/2)} \right] e^{j(\omega_S t - \theta_R - \theta_L)} \end{aligned} \quad (2-8)$$

The rotor current can now be expressed in orthogonal components. Equation (2-8) becomes

$$\bar{I}_R = \left[ I_{RD} + I_{RQ}e^{j(\pi/2)} \right] e^{j(\omega_S t - \theta_R - \theta_L)} \quad (2-9)$$

where

$$I_{RD} = I_{RD} \cos \theta_L + I_{Re} \cos \theta_S \quad (2-10)$$

and

$$I_{RQ} = I_{RD} \sin \theta_L + I_{Re} \sin \theta_S \quad (2-11)$$

When equations (1-10) and (1-11) are substituted into equations (2-10) and (2-11), the rotor components and stator components are related as follows.

The relationship between direct components is,

$$E_{SD} = \frac{3}{2} aKX_R I_{RD} \quad (2-12)$$

The relationship between quadrature components is,

$$E_{SQ} = \frac{3}{2} aKX_R I_{RQ} \quad (2-13)$$

#### ROTOR VOLT-AMPERES (APPARENT POWER)

In order to properly size the power supply feeding the rotor, the volt-ampere requirements of that circuit must be known. This can now be done by making use of the expressions for  $\bar{I}_R$  and  $\bar{V}_R$ .

The rms value squared of rotor current,  $I_R^2$ , can be obtained by inspection of equation (2-9).

$$I_R^2 = \frac{1}{2} (I_{RD}^2 + I_{RQ}^2) \quad (3-1)$$

To obtain a corresponding expression for rotor voltage, equation (1-14) can be expressed in terms of direct and quadrature rotor currents. The result is,

$$\bar{V}_R = \left\{ |Z_R| \left[ I_{RD} + I_{RQ}e^{j(\pi/2)} \right] + E_R e^{-j\theta_R} \right\} e^{j(\omega_S t - \theta_L)} \quad (3-2)$$

In order to obtain the rms value by inspection, the terms within the braces of equation (3-2) must be orthogonal. This can be done by using the identity,

$$e^{-j\theta_R} = \cos \theta_R + (\sin \theta_R)e^{-j(\pi/2)} \quad (3-3)$$

Equation (3-2) becomes

$$\bar{V}_R = \left[ (|Z_R|I_{RD} + E_R \cos \theta_R) + (|Z_R|I_{RQ} + E_R \sin \theta_R) e^{j(\pi/2)} \right] e^{j(S\omega_S t - \theta_L)} \quad (3-4)$$

Since the phasors of equation (3-4) are now separated by  $90^\circ$ , the rms value squared of rotor voltage,  $V_R^2$ , can be written as,

$$V_R^2 = \frac{1}{2} \left( |Z_R|I_{RD} + E_R \cos \theta_R \right)^2 + \frac{1}{2} \left( |Z_R|I_{RQ} + E_R \sin \theta_R \right)^2 \quad (3-5)$$

The rotor volt-amperes can be found by taking the product of equations (3-1) and (3-5),  $V_R^2 I_R^2$ ; the result is

$$V_R^2 I_R^2 = \frac{1}{4} \left[ R_R (I_{RD}^2 + I_{RQ}^2) + \frac{L_S}{a^2 L_R} S E_{SD} I_S \right]^2 + \frac{1}{4} \left[ (1 + K) S X_R (I_{RD}^2 + I_{RQ}^2) + \frac{L_S}{a^2 L_R} S E_{SQ} I_S \right]^2 \quad (3-6)$$

Inspection of equation (3-6) gives the rotor real power,  $P_R$ ; and reactive power,  $Q_R$ .

The second term within each bracket of equation (3-6) is the real and reactive powers transferred between rotor and stator. To show that these same terms appear in stator power expressions, equation (2-3) can be written as follows,

$$\bar{E}_S = \left[ E_{SD} + E_{SQ} e^{j(\pi/2)} \right] e^{j(\omega_S t - \theta_R - \theta_L + \pi/2)} \quad (3-7)$$

The rms value squared of  $\bar{E}_S$ , from equation (3-7), is

$$E_S^2 = \frac{1}{2} (E_{SD}^2 + E_{SQ}^2) \quad (3-8)$$

However, referring back to equation (1-5), it can be seen that the stator induced voltage expands into two components; one related to mechanical speed, another,

to slip speed. It can be shown that an equivalent form of equation (3-8) is the following,

$$E_S^2 = \frac{1}{2} \left[ (1 - S) E_{SD} + S E_{SD} \right]^2 + \frac{1}{2} \left[ (1 - S) E_{SQ} + S E_{SQ} \right]^2 \quad (3-9)$$

When this equation is multiplied by  $I_S^2$ , the result is the apparent (complex) power for the stator circuit; namely

$$E_S^2 I_S^2 = \frac{1}{4} \left[ (1 - S) E_{SD} I_S + S E_{SD} I_S \right]^2 + \frac{1}{4} \left[ (1 - S) E_{SQ} I_S + S E_{SQ} I_S \right]^2 \quad (3-10)$$

When equation (3-10) is compared with equation (3-6), the terms  $S E_{SD} I_S$  and  $S E_{SQ} I_S$  are the real and reactive powers, respectively, that are transferred between rotor and stator. Equation (3-10) gives the stator real power,  $P_S$ ; and the reactive power,  $Q_S$ .

$$P_S = E_{SD} I_S \quad (3-11)$$

$$Q_S = E_{SQ} I_S \quad (3-12)$$

#### SUMMARY

The rotor currents and induced stator voltages are redefined into direct and quadrature components. The quantitative relationship between direct rotor current and direct stator voltage is shown; also, a similar relationship is given for quadrature rotor current and quadrature stator voltage. These components are used to derive expressions for the apparent (complex) power on both the rotor and stator.

This paper, along with the first paper, provide a complete description of rotor and stator variables, as well as the real and reactive power flowing in the doubly-fed generator.

#### REFERENCE

1. F. J. Brady, "A Mathematical Model for the Doubly Fed Wound Rotor Generator," NASA-TM-83454, 1983. IEEE Power Engineering Society, 1983 SM479-3.



1. Report No. NASA TM-83581		2. Government Accession No.		3. Recipient's Catalog No.	
4. Title and Subtitle  A Mathematical Model for the Doubly-Fed Wound Rotor Generator - Part II				5. Report Date	
				6. Performing Organization Code 776-33-41	
7. Author(s)  Frank J. Brady				8. Performing Organization Report No. E-1972	
				10. Work Unit No.	
9. Performing Organization Name and Address National Aeronautics and Space Administration Lewis Research Center Cleveland, Ohio 44135				11. Contract or Grant No.	
				13. Type of Report and Period Covered Technical Memorandum	
12. Sponsoring Agency Name and Address U.S. Department of Energy Wind Energy Technology Division Washington, D.C. 20545				14. Sponsoring Agency Code Report No. DOE/NASA/20320-57	
15. Supplementary Notes Prepared under Interagency Agreement DE-AI01-76ET20320. Prepared for Summer Meeting of the Power Engineering Society sponsored by the Institute of Electrical and Electronics Engineers, Seattle, Washington, July 15-20, 1984.					
16. Abstract  This paper is a mathematical analysis of a doubly-fed wound rotor generator. It is a continuation of a previous paper, which applied the constraints of constant stator voltage and frequency to the circuit equations and obtained expressions for the currents and voltages in the machine. In this paper the previously derived variables are redefined as direct and quadrature components. In addition, the apparent (complex) power for both the rotor and the stator are derived in terms of these redefined components.					
17. Key Words (Suggested by Author(s)) Doubly-fed generator				18. Distribution Statement Unclassified - unlimited STAR Category 33 DOE Category UC-60	
19. Security Classif. (of this report) Unclassified		20. Security Classif. (of this page) Unclassified		21. No. of pages A02	



